B6, B7 3-pole mini contactors – with soldering pins

4 to 5.5 kW AC operated



B6-30-10-P

24



B7-30-10-P

B6..P and B7..P 3-pole mini contactors are compact control products mainly used for switching resistive or motor loads up to 690 V AC.

- These contactors are designed with 3 main poles and one built-in auxiliary contact:
- control circuit: AC operated, low consumption coil (3.5 VA at pull-in and at holding)
 hum-free coil
- contacts configuration 30-01 fulfills the requirements for Mirror contacts acc. to annex F of IEC/EN 60947-4-1
- add-on auxiliary contact blocks for side mounting
- suitable for soldering on PCB boards

| Rated operational power current | | UL/CSA | | Rated control circuit | | Auxiliary | Туре | Order code | Pkg | Weight |
|---------------------------------|-----------|--------|--------|-----------------------|-------|--------------------|------|------------|-----|---------|
| | | motor | use | voltage Uc | | contacts fitted | | | qty | (1 pce) |
| | | | | | | | | | | |
| | θ ≤ 40 °C | rating | rating | 50 Hz | 60 Hz | | | | | |
| 400 V | | 480 V | | | | | | | | |
| AC-3 | AC-1 | | | | | | | | | |
| kW | A | hp | | V AC | V AC |) (| | | | kg |


B6 mini contactors

| 4 | 12 | 3 | 300 V / | 24 | 24 | 1 0 | B6-30-10-P-01 | GJL1211009R0101 | 10 | 0.170 |
|---|----|---|---------|-----------|---------|-----|---------------|-----------------|----|-------|
| | | | 12 A | | | 0 1 | B6-30-01-P-01 | GJL1211009R0011 | 10 | 0.170 |
| | | | | 42 | 42 | 1 0 | B6-30-10-P-02 | GJL1211009R0102 | 10 | 0.170 |
| | | | | | | 0 1 | B6-30-01-P-02 | GJL1211009R0012 | 10 | 0.170 |
| | | | | 48 48 | 48 | 1 0 | B6-30-10-P-03 | GJL1211009R0103 | 10 | 0.170 |
| | | | | | | 0 1 | B6-30-01-P-03 | GJL1211009R0013 | 10 | 0.170 |
| | | | | 110 127 | 110 127 | 1 0 | B6-30-10-P-84 | GJL1211009R8104 | 10 | 0.170 |
| | | | | | | 0 1 | B6-30-01-P-84 | GJL1211009R8014 | 10 | 0.170 |
| | | | | 220 240 2 | 220 240 | 1 0 | B6-30-10-P-80 | GJL1211009R8100 | 10 | 0.170 |
| | | | | | | 0 1 | B6-30-01-P-80 | GJL1211009R8010 | 10 | 0.170 |
| | | | | 380 415 | 380 415 | 1 0 | B6-30-10-P-85 | GJL1211009R8105 | 10 | 0.170 |
| | | | | | | 0 1 | B6-30-01-P-85 | GJL1211009R8015 | 10 | 0.170 |

B7 mini contactors

| 5.5 | 12 | 5 | 600 V / 16 A | 24 | 24 | 1 0 | B7-30-10-P-01 | GJL1311009R0101 | 10 | 0.170 |
|-----|----|---|-----------------|---------|---------|-----|---------------|-----------------|----|-------|
| | | | | | | 0 1 | B7-30-01-P-01 | GJL1311009R0011 | 10 | 0.170 |
| | | | | 42 | 42 | 1 0 | B7-30-10-P-02 | GJL1311009R0102 | 10 | 0.170 |
| | | | | | | 0 1 | B7-30-01-P-02 | GJL1311009R0012 | 10 | 0.170 |
| | | | | 48 | 48 | 1 0 | B7-30-10-P-03 | GJL1311009R0103 | 10 | 0.170 |
| | | | | | | 0 1 | B7-30-01-P-03 | GJL1311009R0013 | 10 | 0.170 |
| | | | | 110 127 | 110 127 | 1 0 | B7-30-10-P-84 | GJL1311009R8104 | 10 | 0.170 |
| | | | | | | 0 1 | B7-30-01-P-84 | GJL1311009R8014 | 10 | 0.170 |
| | | | | 220 240 | 220 240 | 1 0 | B7-30-10-P-80 | GJL1311009R8100 | 10 | 0.170 |
| | | | | | | 0 1 | B7-30-01-P-80 | GJL1311009R8010 | 10 | 0.170 |
| | | | | 380 415 | 380 415 | 1 0 | B7-30-10-P-85 | GJL1311009R8105 | 10 | 0.170 |
| | | | | | | 0 1 | B7-30-01-P-85 | GJL1311009R8015 | 10 | 0.170 |

Other types on request



Main dimensions mm, inches

